



LED bridge driver

12W, 200mA for NUMINOS®, including radio interface for RF module, DALI

Dimmable DALI LED bridge driver with 200mA constant current and an output of 12 Watts including radio interface for the RF module with either Zigbee or Casambi. The LEDs must be connected in series.

TECHNICAL DATA

| | |
|-----------------------------|-------------------|
| Item no. | 1006457 |
| IP Code | IP 20 |
| Assembly | Surface |
| Dimmable | Yes |
| Dimming technology | DALI |
| Primary nominal voltage | 220-240V ~50/60Hz |
| Secondary power / voltage | 150-350 mA |
| Safety class | II |
| Minimum ambient temperature | -20 °C |
| Maximum ambient temperature | 50 °C |
| Level of inrush current | 15.8 A |
| Duration of inrush current | 25.6 µs |
| Color | white |
| Length | 14.18 cm |
| Width | 4.38 cm |
| Height | 3 cm |
| Net weight | 0.14 kg |
| Gross weight | 0.15 kg |
| BIG WHITE Page | 94 |

Accessories

| | |
|---------|---|
| 1006454 | RF module Casambi for LED bridge driver , single colour |
| 1006199 | RF module Zigbee for DALI LED bridge driver , single colour |