



LED gonilnik 40W multi mA

LED gonilnik, neprekinjen tok, 1050mA, 40W, za serijo Numinos Downlight.

TEHNIČNI PODATKI

Št. art.	1004059
Podrobnosti montaže	Trinica za strop
Primarna nazivna napetost	220-240V ~50/60Hz
Sekundarni tok / napetost	800/900/1050 mA
Barva	bela
Risk Group	1
Dolžina	14.7 cm
Širina	4.3 cm
Višina	3 cm
Neto teža	0.14 kg
Bruto teža	0.151 kg
BIG WHITE Stran	94