



QR111 RETROFIT LED

lamp, G53, 2700K, 25°, white

High-performance LED LV reflector lamp as an ideal replacement for LV halogen lamps with G53 socket. This LED lamp is also ideal for use in general lighting applications. LED floodlights create a warm light beam, comparable with halogen lamps, and are ideal for accent and room lighting. LED lamps are compatible with most existing lights with a G53 socket and have been developed specially as replacements for halogen bulbs. LED lamps provide increased energy savings and much lower maintenance costs. Only possible to operate with a conventional transformer. The product has an energy efficiency index of A+. The weighted consumption is 12kWh/1000h.

TECHNICAL DATA

| Item no. | 560652 |
|-----------------------------|--------------|
| Socket | G53 |
| Lamp type | LED G53 |
| IP Code | IP 20 |
| Lamp mercury content | 0 mg |
| Nominal voltage | 12V ~50Hz V |
| Weighted energy consumption | 10 kWh/1000h |
| Electrical power factor | 0.592 |
| Wattage | 9 W |
| Starting time | 0.5 s |
| Start time | 0 s |
| Ambient temperature | 25 °C |
| Minimum ambient temperature | -20 °C |
| Maximum ambient temperature | 40 °C |
| Lumen | 800 lm |
| Colour temperature | 2700 Kelvin |
| Beam angle | 25 ° |
| Color | white |
| CRI | 80 |
| Lumen | 70 lm |
| Binning | 6 SDCM |
| Service life | 25000 h |
| | |



| Switching cycles | 25000 |
|------------------|----------|
| Width | 11.1 cm |
| Height | 5.4 cm |
| Depth | 11.1 cm |
| Diameter | 11.1 cm |
| Net weight | 0.13 kg |
| Gross weight | 0.185 kg |